

Anritsu Advancing beyond

Signal Quality Analyzer-R

32G/64G NRZ/PAM4 Signal Integrity Test Solution*

MP1900A

 **SQA-R**



*: Refer to the MP1900A PCIe/USB/Thunderbolt/Display Port Test Solution Catalog (MP1900A-E-A-1) for the information on MP1900A high-speed-bus test solution.



apliquem uO

One Box over 400G Testing

MP1900A

Signal Quality Analyzer-R



Automation
Function
PCIe1-6


Data center and network traffic volumes are increasing exponentially as mobile networks start upgrading to 5G and 'Big Data' applications become popular. As a consequence, physical-layer devices are required to support faster transmission speeds, larger data capacities, and assured signal quality, in turn making signal integrity analysis ever more important. To meet these needs, Anritsu has implemented more accurate signal integrity tests, such as bit error rate (BER) measurements, crosstalk tests, Jitter Tolerance tests, etc., in its MP1900A test solution for 64 Gbaud NRZ/PAM4.

All-in-One Futureproof Measurements

The Signal Quality Analyzer-R MP1900A series is a modular 8-slot high-performance BERT. Installing multiple modules in the slots not only supports today's 400 GbE analysis requirements, but also provides futureproof support for next-generation 800G measurements.



World-Leading Highest Level Waveform Output Quality Resulting
from Fast Tr/Tf and Low Intrinsic Jitter.



One Box over
400G Testing



Beyond 400 GbE Expectations

High-Quality Waveforms, and High-Sensitivity Input

Higher Measurement Efficiency Supported by Industry-beating Signal Quality, High Sensitivity, And Wide Bandwidth

- High-speed Tr/Tf of 8.5 ps (20 to 80%)
- Low Intrinsic Jitter of 170 fs (rms)
- Low noise and low distortion high-quality data output
- 116-Gbit/s PAM4 error-free measurements using high-sensitivity and wideband Rx performance

High Transmission Capacity and Excellent Expandability

Futureproof Multichannel Expansion for 800G R&D

- All-in-one support for 512 Gbit/s max. transmission capacity
- Multichannel expandability 4ch PAM4/NRZ
- 8 slots for module addition
- Jitter and noise module expandability
- Operation baud rates of 2.4 Gbaud to 64.2 Gbaud

World-First All-in-One PAM4 BER Test Solution

Easy-to-Setup and Operate All-in-One PAM4 Bit Error/FEC Symbol Error Measurement System

- Supports Emphasis variable dynamic range (± 20 dB) and ISI simulation
- 4-level linearity control
- Built-in Clock Recovery, Equalizer
- Jitter Tolerance Test, Bathtub Jitter Analysis
- PAM4 Pattern Editor, Symbol Error Measurement
- Real-time FEC Symbol Error and FEC Based Jitter Tolerance Measurements
- FEC Pattern Generation, Error Analysis using FEC Symbol Capture Function
- Jitter Tolerance measurement using DUT BER counter function
- Automatic Margin measurement using Eye contour
- Automatic pattern mismatch detection and optimum Equalizing using Auto Search
- PCIe1-6 Link training

Target Standards

- Ethernet , 800/400/200/100/50 GbE
- CEI-56G, CEI-112G
- InfiniBand-HDR
- 64G Fibre Channel
- PCIe 1-7


Target DUT

- Optical module (QSFP-DD, OSPF, CFP8, SFP56)
- TOSA, ROSA, SERDES
- Active Optical Cable (AOC)
- PCI-Express Device, System


High-Quality Waveforms PAM4 PPG

High-Quality Data Output with High-Speed Tr/Tf and Low Intrinsic Jitter


The PAM4 PPG MU196020A supports high-quality data output with low noise and low distortion over high analog band with Tr/Tf of 8.5 ns and Intrinsic Jitter of 170 fs rms. High-reproducibility measurement supported by PAM4 signals with open 3-Eye waveform. Additionally, Emphasis and Linearity control functions optimize PAM4 data output to DUT.



58 Gbaud NRZ



53.125 Gbaud PAM4




58 Gbaud PAM4

Typical Output Waveform (J1789A 40 cm Cable, 1400 mV Differential, PRBS15)


4Tap Emphasis Output at 20 dB max.

The 4Tap Emphasis function (MU196020A-011) can generate the Pre-Emphasis and De-Emphasis signals required by each standard for maximum rates of 64.2G. Since each tap can be changed independently up to 20 dB, corrected waveforms for various transmission paths can be output with good reproducibility.




Pre-Emphasis/De-Emphasis Optimization Effects


In addition, using the Channel Emulator and ISI functions* makes it easy to output waveforms with simulated channel loss for high-speed devices, as well as waveforms corrected for loss. As a result, not only is testing of multiple channel boards unnecessary, but also high-reproducibility channel-loss-dependent tests of high-speed device performance are easy, helping shorten development times.




Channel Emulator and ISI Functions



Emulates Channel Loss or generates Loss calibration signal (MU196020A-040)



NRZ CEI-28G 14 dB loss



PAM4 26.6G 4 dB loss



PAM4 26.6G 6 dB loss


ISI Function Typical Waveform

High-Quality Waveforms PAM4 PPG


Freely Control PAM4 Output Linearity

The PAM4 PPG can freely control the PAM4 output linearity to change the output level for each Eye independently.

As well as correcting the output waveform of non-linear devices, a PAM4 waveform with variable RLM (Ratio of Level Mismatch) can be output with good reproducibility.




Waveform with Controlled Linearity



PAM4 Output Setting

PAM4 Pattern Editor

PAM4 evaluation test patterns (SSPRQ, PRBS13Q, PRBS31Q, etc.) are built-in as standard. Versatile pattern output settings, such as MSB/LSB bit inversion, Gray Code ON/OFF, Precoder ON/OFF, and a Bit Shift function (changes MSB bit phase by ± 256 bits) support combined use of various DUT internal error counters and analysis of error occurrence locations.



FEC Pattern Generation

These MU196020A-042 (RS-FEC) and -043 (PCIe6 FEC) options generate FEC patterns and add FEC errors, respectively. Moreover, the FEC Error Addition function evaluates the DUT FEC error correction ability. The following FEC pattern can be used.

PAM4


- RS-FEC Scrambled Idle 50G 1 Lane (26.5625 Gbaud, 50GBASE-KR/CR/SR/FR/LR)
- RS-FEC Scrambled Idle 100G 1 Lane (53.125 Gbaud, 100GBASE-DR/KR1/CR1)
- RS-FEC-Int Scrambled Idle 100G 1 Lane (53.125 Gbaud, 100GBASE-P)
- RS-FEC Scrambled Idle 100G 2 Lanes (26.5625 Gbaud, 100GBASE-KR2/CR2/SR2)
- RS-FEC Scrambled Idle 200G 4 Lanes (26.5625 Gbaud, 200GBASE-SR4/DR4/FR4/LR4)
- RS-FEC Scrambled Idle 200G 2 Lanes (53.125 Gbaud, 200GBASE-KR2/CR2)
- RS-FEC Scrambled Idle 400G 4 Lanes (53.125 Gbaud, 400GBASE-DR4/KR4/CR4)
- RS-FEC Scrambled Idle 400G 8 Lanes (26.5625 Gbaud, 400GBASE-FR8/LR8)
- NOP Flit Layout in x1-x16 Link

NRZ


- RS-FEC Scrambled Idle 25G 1 Lane (25.78125 Gbaud, 25GBASE-KR/CR/SR/LR/ER)
- RS-FEC Scrambled Idle 100G 4 Lanes (25.78125 Gbaud, 100GBASE-KR4/CR4/SR4)

116-Gbit/s PAM4 Signal Error-Free BER Measurement using High Input Sensitivity Function


Combining the PAM4 ED MU196040B with the PAM4 PPG supports BER measurements of 116-Gbit/s (58 Gbaud) PAM4 signals. Error-free BER measurement is achieved by the industry-best high sensitivity performance of 23 mV @26 Gbaud and 36 mV @53 Gbaud. The resulting high-accuracy BER measurements make it easy to troubleshoot previously difficult-to-analyze PAM4 devices. In addition, true DUT performance can be verified because even CEI-112G-VSR-defined worst-case stressed signals can be received at low-error rates (<E-8), exceeding the specifications.



Error-Free Measurement of PAM3 Signals at 23 mV @26 Gbaud, and 36 mV @53Gbaud




CEI-112G-VSR-defined Worst-Case Stressed PAM4 Signal



PAM4 BER Measurement Screen

Moreover, even the BER of Eye waveforms closed by ISI can be measured using the built-in Equalizer function.




Built-in Clock Recovery

An optional Clock Recovery function (MU196040B-021, 022, 023) can be installed in the PAM4 ED, eliminating both the need for an external clock recovery unit, and phase adjustment of the ED Data/Clock. Jitter Tolerance tests of PHY devices, such as QSFP-DD and SERDES with different Tx and Rx signal clocks, as well as BER measurements of AOC device are supported for the ideal, high cost-performance test solution.


High-Sensitivity, Wideband PAM4 ED

Symbol Error Rate (SER) Evaluation

Since the error rate at each symbol (0 to 3) of the PAM4 signal can be confirmed, error occurrence locations can be analyzed in more detail (MU196040B-041).



PAM4 Symbol Image



Error Rate Measurement Screen per Symbol Error Level


Auto-Search Function

In addition to the Upper, Middle, and Lower Eye measurement points (voltage threshold value and phase), automatic detection of the optimum Equalizer setting automatically detects the conditions required for the best BER results. Moreover, automatic detection of the PAM4 Symbol Logic and Gray Coding conditions supports automatic evaluation of pattern conditions for the input PAM4 Symbol coding, providing a more efficient measurement environment.




Diagnostics Mode Function

This function is for troubleshooting logic errors, such as inverted logic, and bit skew between the MSB and LSB. When these types of logic errors prevent synchronization, the cause can be specified from the MSB and LSB error results, and from the bit skew detection result.



Capture Function

Input test-pattern data can be captured in blocks of up to 8 Mbits (4 million symbols) for input and analysis of results. The captured test pattern is displayed as lines of symbol patterns with color-coded errors for easy analysis.



Color-Coded Error Capture Screen

Logging Function


Changes in DUT performance and stability over time can be evaluated by saving measurement results, such as ER/EC, periodically.



BER/SER Results Logging Screen


Real-time FEC Symbol Error and FEC Based Jitter Tolerance Measurement Functions

Uncorrectable Codeword and FEC Symbol Errors can be measured and displayed on one screen in real-time simultaneously with bit error measurements. Measurement of jitter tolerance and FEC Symbol Error per codeword distribution based on correctable/uncorrectable FEC is supported (MU196040B-042). Both bit error and FEC Symbol Errors are measured at high speed.



FEC Symbol Capture Function


The input data is captured when the number of FEC symbol errors exceeds the threshold setting based on the 400 GbE-defined FEC symbols and Codeword length. The causes of FEC-uncorrectable errors can be analyzed from the captured data (MU196040B-041).



Capturing Detected FEC Symbols Errors


FEC Analysis Decode Function

Supports Gray decode of input signal and 1/(1 + D) Mod4 decoding to measure FEC Symbol Errors.



PAM4 Bathtub Jitter Analysis


The input signal jitter and phase margin can be measured automatically using the Bathtub function. The wideband and high-sensitivity PAM4 ED helps more accurate measurement of DUT performance.



Example of PAM4 Signal Bathtub Measurement

Eye Contour

The input signal Eye opening is measured at high speed based on the Bathtub estimate. In addition to NRZ, the PAM4 Symbol Upper, Middle, and Lower Eye openings are measured, supporting more accurate evaluation of Eye Margin characteristics at BER estimates up to E-20.



One Box PAM4 BER Test Solution

All-in-One Measurement Solution

8-slot main unit accommodates various modules, including PPG/ED, synthesizer, Jitter modulation source, and noise generator. A compact, high cost-performance, next-generation, all-in-one measurement solution can be configured without other external instruments.



MP1900A

12.5 GHz 4 Port Synthesizer MU181000B

Jitter Modulation Source MU181500B

Re-Driver MU196060A

PAM4 ED MU196040B/SI ED MU195040A

PAM4 PPG MU196020A

Noise Generator MU195050A

★: Refer to the MP1900A Selection Guide for details of supported multichannel configurations and module combinations.
Consult your sales representative for module configurations not described in the MP1900A Selection Guide.

64 Gbaud All-in-One NRZ/PAM4 BER Measurement

BER can be measured in real-time without using external equipment. In addition, permits error evaluation at each PAM4 symbol.

- World-first all-in-one solution without requiring external equipment
- Baud rates of 2.4 Gbaud to 58.2 Gbaud (PAM4)/64.2 Gbaud (NRZ)
- Module with built-in Clock Recovery (MU196040B-021, 022, 023), 2.4 Gbaud to 32.1 Gbaud, 51 Gbaud to 58.2 Gbaud
- PAM4 Symbol BER evaluation (MU196040B-041)
- Real-time FEC Symbol Error(MU196040B-042) and FEC Based Jitter Tolerance Measurements

Error Rate Measurement Screen for Each Symbol Level

MP1900A

PAM4 PPG MU196020A

Synthesizer MU181000B

PAM4 ED MU196040B

PAM4

PAM4

DUT

Jitter Tolerance Measurement using DUT BER Counter (MX183000A-PL031)

When the DUT has a bit error counter, combination with the MP1900A PPG makes it easy to configure a highly cost-effective Jitter Tolerance measurement environment.

JTOL Measurement Screen

MP1900A

PCB Trace

DUT

Measure Jitter Tolerance using captured error count


Capture error count via USB or Ethernet connection

One Box PAM4 BER Test Solution


Versatile Jitter/Noise Addition Function for Jitter Tolerance Tests without Other External Equipment (MX183000A-PL001)

The DUT receiver input stress tolerance test measures the BER under the worst conditions using a stressed signal with added jitter and voltage noise. Adding the Jitter Modulation Source MU181500B and MU195050A for adding CM/DM/White Voltage Noise to the MP1900A series supports all-in-one receiver stress tests for various interface standards. Using the MP1900A high-quality signal prior to jitter and noise addition along with the high-linearity jitter and noise addition function offers powerful support for receiver stress tolerance tests.


- Easy Jitter Tolerance measurement
- PHY device Jitter Tolerance test with impressed SJ/RJ/BUJ
- Mask measurements supporting various standards
- Shorter measurement times using low error rate (1E-12, 1E-15, etc.) estimation function
- Tolerance measurement for device characteristics using four Binary, Upward, Downward, and Binary + Linear measurement methods
- Built-in Jitter Tolerance Mask standards for 200/400G including IEEE 802.3, CEI, etc.
- Support for both user-defined masks and new standards




PAM4 Signal Jitter Tolerance Test using One MP1900A




Sine Wave Jitter (SJ)



Random Jitter (RJ)



CM/DM Noise



White Noise

Jitter/Noise Types*


*: The upper noise addition rate is 32.1G.

One Box PAM4 BER Test Solution

All-in-One Ethernet/PCIe Measurement

Both PAM4 and increasingly faster PCIe 1-7 interfaces can be measured using this all-in-one test solution. Protocol Aware Link training* is supported up to PCIe 6.0 along with PAM4 Symbol Error measurements and Jitter Tolerance tests, helping play a key role in first-stage PCIe certification.




*: For details, refer to the Selection Guide (MP1900A-E-Z-1)



High Transmission Capacity and Excellent Expandability


Easy Multichannel Measurement Support

The MP1900A series is an 8-slot, modular, high-performance BERT. Installing multiple 64G PAM4 PPG module boards in the slots provides the performance for measuring not only 400 GbE systems but also future 800 GbE systems as well. This flexible expandability helps customers maximize product development-cost efficiencies and bring products to market early.




Supports 64G × 4ch Output Pattern Synchronization

Pattern synchronization for each channel ideal for all-at-once evaluation of parallel interfaces, Crosstalk and Skew tolerance evaluation, D/A converter evaluation and FEC pattern evaluation.




Inter-lane Skew Adjustment and Crosstalk Tests

The phase of each channel can be controlled independently using the option (MU196020A-030). The precision control in 2-mUI steps supports high-accuracy testing of DUT crosstalk characteristics.



PAM4 PPG/ED Application Example

PAM4 SERDES IC, CDR IC Evaluations



Required Test Items

- Stress Test
- BER and FEC Based Jitter Tolerance Tests

All-in-One Built-in Stress Test Function

Accurate evaluation of the Rx performance of PHY layer ICs used in high-speed servers, optical transceivers, and Active Optical Cables (AOCs) requiring good compatible connectivity requires correction of the signal performance at the test board input connector. When evaluating ICs supporting various protocols, the stress signal including transmission path loss, jitter, etc., must be corrected for various cases according to the specifications. However, changing the cables, test board, and components connected to the PPG for each protocol is time consuming, lowers work efficiency, and has issues with unstable measurement results.

The MP1900A have built-in ISI, Noise, Jitter, Crosstalk, Emphasis, and Clock Recovery functions required for NRZ and PAM4 signal stress tests to support easy and high-reproducibility evaluations using the all-in-one MP1900A.

Jitter Tolerance Test

Supports addition of various jitter types (SJ1/2, RJ, BUJ, SSC) to the PAM4 PPG output (MU181500B). In addition, the PAM4 ED has a built-in Clock Recovery required for Jitter Tolerance tests as well as high sensitivity and wide analog bandwidth performance for receiving low-amplitude and closed-Eye data signals to support high-reproducibility Jitter Tolerance tests. In addition, measurement based on correctable/uncorrectable FEC is supported.

Burst Error Analysis using Real-time FEC Symbol Error Measurement and FEC Symbol Capture Functions


Uncorrectable Codeword and FEC Symbol Errors can be measured and displayed on one screen in real-time simultaneously with bit error measurements. The FEC symbol capture function captures input data when the number of FEC Symbol Errors exceeds the set threshold.

The input data is captured when the number of FEC symbol errors exceeds the threshold setting. The causes of FEC-uncorrectable errors can be analyzed from the captured data.

PAM4 PPG/ED Application Example

TOSA, Driver IC Evaluations

Since the test-signal performance affects the IC performance at evaluation of parts such as TOSA and driver ICs used by optical transceivers requiring analog high-frequency performance, a reference test signal source with fast Tr/Tf and low Intrinsic Jitter is required.



Required Test Items

- Multi-channel synchronous measurement
- Optimized TOSA TDECQ value using Emphasis and Linearity settings

Simultaneous Multichannel Measurement of 4ch max. with One MP1900A

Optical transceiver modules specified as 200 GbE/400 GbE achieve high bit rates using either a 4- or 8-lane optical interface. The MP1900A main unit can accommodate four PAM4 PPG boards and four ED boards in four slots each to perform simultaneous 4ch parallel measurement of multilane integrated optical parts and driver ICs, helping shorten measurement times.


Optimized TOSA TDECQ value using Emphasis and Linearity settings

The TDECQ value is a specific measurement item at 200 GbE/400 GbE PAM4 TOSA evaluation.

The TDECQ value is dependent not only on the signal waveform quality but also on the test signal Emphasis setting and 4-level linearity. Consequently, to examine the true ability, both a high-quality signal source and Emphasis and linearity control functions are required to evaluate the TDECQ characteristics for each setting. The PAM4 PPG MU196020A has built-in Emphasis and linearity control functions supporting high-quality data output with its high Tr/Tf speed and low Intrinsic jitter, which is sufficient for TDECQ optical output evaluation. The functions and performance required for PAM4 signal evaluation are implemented with high-quality waveforms optimized for evaluating TOSA and driver, etc., ICs. Evaluation of TOSA, driver ICs, etc., optimized by implementing functions and performance required for evaluating PAM4 signals using high-quality waveforms. In addition, connecting MP2110A oscilloscope automatically sets optimum Emphasis for TOSA optical signal TDECQ value.

PAM4 PPG/ED Application Example

Optical Module Evaluation



Required Test Items

- Simultaneous 4ch BER Measurement
- Optical output waveform optimized using Emphasis and Linearity Control
- Skew and Crosstalk Tests
- Jitter Tolerance Test

400-GbE (53G × 4λ) PAM4 BER Measurements

IEEE 802.3 200 GbE/400 GbE EML and optical modules can be evaluated.
Multilane evaluation of 4ch EML is supported by simultaneous and independent driving.

Optical Output Waveform Optimization using Emphasis and Linearity Control

The linearity and crosstalks of each Eye on the screen can be adjusted easily using the 4Tap Emphasis up to 20 dB and PAM4 output linearity control function for fast and high-reliability evaluation.

Skew and Crosstalk Test

Applications using 30-Gbaud class signals require testing using actual equipment as well as logic testing.
With pattern synchronization and variable phase functions, the MP1900A easily supports the tests, such as Rx device skew tolerance, crosstalk effect, etc.

Jitter Tolerance Test


With built-in Clock Recovery required for Jitter Tolerance tests, the PAM4 ED can receive low-amplitude, closed-Eye data signals using its high-sensitivity and wide analog band functions to support high-reproducibility Jitter Tolerance tests.

PAM4 PPG/ED Application Example


Multilane FEC Evaluation

FEC can be evaluated by combining the FEC pattern generation, error insertion, and reading the DUT bit error count.

Evaluating Optical FEC Signal Transmission



Evaluating Electrical FEC Signal Transmission



Required Test Items

- Generates 1, 4, 8ch FEC patterns
- Inter-lane Skew Adjustment Test and Crosstalk Test
- Executes Jitter Tolerance tests using FEC patterns
- FEC Analysis Assistance using ED Capture Function

400 GbE Evaluation

IEEE 802.3-specified 400 GbE SERDES FEC evaluation is supported by simultaneous and independent driving of 1, 4, 8ch FEC pattern data output from the all-in-one MP1900A.

And Captures uncorrectable errors from DUT using DUT error counter read function and displays results at MP1900A.

Inter-lane Skew Adjustment Test and Crosstalk Test

FEC decoding is performed after first adjusting the inter-lane skew of the received signal in SERDES.

Since the MP1900A generates signals for the number of lanes and can generate skew of ± 64 UI for each lane, it is ideal for testing inter-lane skew adjustment. Additionally, the MP1900A has pattern synchronization and variable phase functions, and easily supports the tests, such as Rx device skew tolerance, crosstalk effect, etc.

Jitter Tolerance Test

Jitter is impressed on the FEC pattern generated by the MP1900A and SERDES uncorrectable errors are read to implement Jitter Tolerance tests with FEC patterns.


FEC Analysis Assistance using ED Capture Function

Generally, RS-FEC (544, 514) is used for 200 GbE/400 GbE, and RS-FEC (528, 514) is used for 25 GbE.

To understand whether errors generated in the transmission line can be corrected or not by FEC, it is important to both count the number of errors and report the error distribution. Additionally, signal analysis helps understand whether errors occur easily when each symbol transitions in some way. The MP1900A has a function for capturing and displaying received signals by using errors as a trigger. In addition to reporting the error distribution using this function, it is also easy to understand what error is generated by which symbol transition.

PAM4 PPG/ED Application Example

Active Cable Evaluation



Required Test Items

- 8ch Simultaneous PAM4 BER Measurement (4ch both ways)
- Crosstalk Test
- Jitter Tolerance Test

8ch Simultaneous PAM4 BER Measurement (4ch both ways)

QFSP-type Active Optical Cables (AOC) used by 200 GbE, etc., use 4ch transmission in both directions to achieve simultaneous 8ch transmission. The MP1900A can measure 8ch (8ch PPG + 8ch ED) simultaneously for both excellent performance and shorter measurement time.

Crosstalk Test

Applications using 30-Gbaud class signals require testing using actual equipment as well as logic testing. With pattern synchronization and variable phase functions for each channel, the MP1900A easily supports the tests, such as the impact of AOC crosstalk, etc.

Jitter Tolerance Test

AOCs in data centers are increasingly switching to low I/O amplitude levels to cut power consumption, increasing the importance of interconnectivity. With built-in Clock Recovery required for Jitter Tolerance tests, the PAM4 ED can receive low-amplitude, closed-Eye data signals using its high-sensitivity and wide analog band functions to support high-reproducibility Jitter Tolerance tests.

W1 (1.0 mm) 110-GHz Components

This line of components is for ultra-high-speed signals exceeding 100 GHz.
Future ultra-high-speed signal interfaces are supported by attenuators, dividers, DC blocks, cables, and Bias Tees with a W1 connector.



Attenuators	
41W-X* Series	Precision Fixed Attenuator, 3 dB, DC to 110 GHz, W1 (m)-W1 (f), 50Ω
	Precision Fixed Attenuator, 6 dB, DC to 110 GHz, W1 (m)-W1 (f), 50Ω
	Precision Fixed Attenuator, 10 dB, DC to 110 GHz, W1 (m)-W1 (f), 50Ω
Power Divider	
W240A	Precision Power Divider, DC to 110 GHz, W1 (f) input, W1 (f) outputs, 3 resistor, 50Ω
Power Splitter	
W241A	Precision Power Splitter, DC to 110 GHz, W1 (m) input, W1 (f) outputs, 2 resistor, 50Ω
DC Block	
W265	Precision Ultra Wide Band DC Block, 50 kHz to 110 GHz
Cables	
3670W50A-1	Test Port Cable, Armored, Semi-rigid, DC to 110 GHz, W1 (m)-W1 (f), 10 cm
3650W50A-2	Test Port Cable, Armored, Semi-rigid, DC to 110 GHz, W1 (m)-W1 (f), 16 cm
Bias Tees	
W255FM	Precision Ultra Wide Band Bias Tee, 50 kHz to 110 GHz, W1 (f), W1 (m) output, SMC (m) bias
W255MF	Precision Ultra Wide Band Bias Tee, 50 kHz to 110 GHz, W1 (m), W1 (f) output, SMC (m) bias
W252MF	Ultra Wide Band Kelvin Bias Tee, 100 MHz to 110 GHz, W1 (m) input, W1 (f) output, SMC (m) bias and sense
W252FM	Ultra Wide Band Kelvin Bias Tee, 100 MHz to 110 GHz, W1 (f) input, W1 (m) output, SMC (m) bias and sense

*: X is replaced by the attenuation level value


Panel Layout

Signal Quality Analyzer-R MP1900A

Front Panel



Rear Panel




- 1 Ground Jack**
Wrist strap to discharge static electricity
- 2 USB Port**
Four USB2 ports for connecting peripherals
- 3 Power Switch**
Switches power on and off; Standby LED over power switch lights when power cord connected and Power switch set to off
- 4 Function Keys**
Keys for defining functions using software
- 5 HDD Access LED**
Lamp that lights during access to built-in HDD
- 6 Rotary Encoder**
Switch to increase/decrease numeric values by turning knob
- 7 GPIB**
GPIB Connector
- 8 HDD**
Slot for secondary 2.5" HDD
- 9 Ethernet Connector**
External: For Remote Control
(Internal: Reserved for future function expansion)
- 10 USB Port**
Two USB3.0 ports for peripherals
- 11 HDMI**
HDMI connector for displaying screens on external screen
- 12 Power Inlet**
Socket for connecting 3-pole power cord to supply 100 VAC to 12 VAC or 200 VAC to 240 VAC power
- 13 VGA**
VGA connector for displaying screens on external screen
- 14 Frame Ground Terminal**
Terminal for discharging electrostatic charges; connect DUT and common ground using ground strap

Panel Layout

Modules

21G/32G bit/s SI PPG MU195020A



1 Data Output, $\overline{\text{Data}}$ Output

Connectors outputting differential Data and $\overline{\text{Data}}$ signals

2 Gating Out, $\overline{\text{Gating}}$ Out

Repeat: Timing signal output

Burst: Timing signal output used at Burst

3 Aux In

Auxiliary signal input connector

Either Error Injection or Burst can be selected.

4 Aux Out, $\overline{\text{Aux}}$ Out

Auxiliary signal output connectors

Output of any of 1/N Clock, Pattern Sync, and Burst2 can be selected.

5 Clock Out

Clock signal output connector

6 Ext Clock In

Clock signal input connector

21G/32G bit/s SI ED MU195040A



1 Data Input, $\overline{\text{Data}}$ Input

Input connectors for Data and $\overline{\text{Data}}$ signals

Supports both differential and single inputs

When the Clock Recovery MU195040A-x22 is installed, the clock is recovered from the signal input to Data Input1.

2 Aux In

Auxiliary signal input connector

Any of External Mask, Burst, and Capture External Trigger can be selected.

3 Aux Out, $\overline{\text{Aux}}$ Out


Auxiliary signal output connectors

Any of 1/N Clock, Pattern Sync, Error, Sync Gain can be output.

4 Ext Clock In

Clock signal input connector

PAM4 PPG MU196020C



1 Data Output, $\overline{\text{Data}}$ Output

Connectors outputting differential Data and $\overline{\text{Data}}$ signals

2 Gating Out

Repeat: Timing signal output

Burst: Timing signal output used at Burst

3 Aux In

Auxiliary signal input connector

Either Error Injection or Burst can be selected.

4 Aux Out, $\overline{\text{Aux}}$ Out

Auxiliary signal output connectors

Output of any of 1/N Clock, Pattern Sync, and Burst2 can be selected.

5 Clock Out

Clock signal output connector

6 Ext Clock In

Clock signal input connector

Panel Layout

Modules

PAM4 ED MU196040B




- 1 Data Input, Data Input**
Input connectors for Data and Data signals
Supports both differential and single inputs

2 Aux In
Auxiliary signal input connector
Any of External Mask, Burst, and Capture External Trigger can be selected.
- 3 Aux Out, Aux Out**
Auxiliary signal output connectors
Any of 1/N Clock, Pattern Sync, Error, Sync Gain can be output.

4 Ext Clock In
Clock signal input connector

Noise Generator MU195050A



- 1 Data Output, Data Output**
Connector for outputting differential Data and Data Signal with added noise

2 Data Input, Data Input
Connector for inputting Data and Data signal with added noise
- 3 External Input, External Input**
External noise input connectors

* Input2 and Output2 are not used by the MU196020A

Noise Generator MU196050B



- 1 Noise Output, Noise Output**
Connector for outputting differential Data and Data Signal with added noise

2 External Input, External Input
External noise input connectors

32G baud NRZ/PAM4 Re-Driver MU196060A



- 1 Data Output, Data Output**
Connectors for outputting equalized differential Data and Data signals

2 Data Input, Data Input
Connectors for inputting differential Data and Data signals
- 3 Clock Output**
Connector for outputting Clock signal recovered from input data

Panel Layout


Modules

Synthesizer MU191000A



- 1 10 MHz Ref Output**
Output 10 MHz clock for reference
- 2 10 MHz Ref Input**
Inputs 10 MHz clock for reference
- 3 100 MHz Ref Input**
Inputs 100 MHz clock for reference
- 4 AUX Output**
Output for auxiliary signal
- 5 Clock Output 1 to 4**
Outputs clocks

Jitter Modulation Source MU181500B



- 1 IQ Output**
Outputs IQ signal
- 2 Ext Jitter Input**
Inputs Jitter Modulation Source
- 3 Sub-rate Clock Output**
Differential Clock Output signal generated from 1/8 to 1/256-divided Clock Output based on any of following Clock inputs
• Ext Clock Input • Aux Input
- 4 Aux Input**
Inputs clock signal
- 5 Reference Clock Output**
Dual-system Clock Output signal generated from either 1/1, 1/2, or 1/4-divided Jitter Clock Output based on any of following Clock inputs
• Ext Clock Input • Aux Input
- 6 Jittered Clock Output**
Two outputs jitter modulated clock signal
- 7 Ext Clock Input**
Inputs external clock

28G/32G bit/s PPG (1ch or 2ch) MU183020A



- 1 Data1/Data1 Output^{*1}**
Output for 1ch differential data signal
- 2 Data2/Data2 Output^{*2}**
Output for 2ch differential data signal
- 3 Gating Output**
Output for burst timing signal
- 4 Aux Input**
Input for auxiliary signal
- 5 Aux/Aux Output**
Output for differential auxiliary signal
- 6 Clock Output**
Output for clock signal
- 7 Ext Clock Input**
Input for external clock signal

*1: Data/Data when 1ch option was selected.

*2: Not implemented when 1ch option was selected.

28G/32G bit/s High Sensitivity ED (1ch or 2ch) MU183040B



- 1 Data1/Data1 Input^{*3}**
Input for 1ch differential data signal
- 2 Data2/Data2 Input^{*4}**
Input for 2ch differential data signal
- 3 Aux Input**
Input for auxiliary signal
- 4 Aux/Aux Output**
Output for differential auxiliary signal
- 5 Ext Clock Input**
Input for external clock signal

*3: Data/Data when 1ch option was selected.

*4: Not implemented when 1ch option was selected.

Signal Quality Analyzer-R MP1900A Specifications

Refer to the [MP1900A Data Sheet](#) for detailed specifications.

Signal Quality Analyzer-R MP1900A

LCD		12.1" WXGA 1280 × 800
Remote Interface		GPIO, LAN
Module Slots		8
External Equipment Interface		USB × 6, VGA × 1, HDMI × 1
OS		Window 10
Power Supply		100 V(ac) to 120 V(ac), 200 V(ac) to 240 V(ac), 50 Hz to 60 Hz Power consumption: 1350 VA max.
Dimensions and Mass		340 (W) × 222.5 (H) × 451 (D) mm, 20 kg (excluding modules)
CE	EMC	2014/30/EU, EN61326-1, EN61000-3-2
	LVD	2014/35/EU, EN61010-1
	RoHS	2011/65/EU, (EU) 2015/863, EN IEC 63000: 2018
UKCA	EMC	S.I. 2016 No.1091, EN 61326-1, EN61000-3-2
	LVD	S.I. 2016 No.1101, EN 61010-1
	RoHS	S.I. 2012 No.3032, EN IEC 63000:2018

Synthesizer MU191000A

Clock Output	Number of Outputs: 4 Frequency Setting Range: 0.1 GHz to 16.05 GHz (Clock accuracy and stability depend on the internal reference clock of the MP1900A main unit or an external reference clock input.) Amplitude Level: 0.7 Vp-p ±0.3 Vp-p (0.4 Vp-p to 1.0 Vp-p) Connector: SMA (J), Termination: 50Ω/AC Coupling
10 MHz Reference Input	Frequency Range: 10 MHz ±2 ppm Connector: SMA (J), Termination: 50Ω/AC Coupling
10 MHz Reference Output	Level: 1.0 Vp-p ±0.3 Vp-p (0.7 Vp-p to 1.3 Vp-p) Connector: SMA (J), Termination: 50Ω/AC Coupling
100 MHz Reference Input	Frequency Range: 100 MHz with SSC 30 kHz to 33 kHz Center/Down Spread 0 to 5000 ppm Amplitude: 0.15 Vp-p to 1.45 Vp-p Connector: SMA (J), Termination: 50Ω/AC Coupling
AUX Output	SMA (J), Termination: 50Ω/AC Coupling (Always apply a 50Ω termination to ensure proper operation.)
Internal SSC Modulation	SSC 33 kHz Center/Down Spread Selectable OFF/1500 ppm/3000 ppm/5000 ppm Selectable (PCIe 1 to 7 supported)

12.5 GHz 4 Port Synthesizer MU181000B

Clock Output	Number of Output: 4 Frequency Range: 0.1 GHz to 12.5 GHz, Steps: 1 kHz/1 MHz Level: 0.4 Vp-p to 1 Vp-p (AC) Connector: SMA (J), Termination: 50Ω/GND
10 MHz Input	Frequency: 10 MHz ±10 ppm Level: 0.5 Vp-p to 2.0 Vp-p Connector: BNC, Termination: 50Ω/GND
10 MHz Output	Level: 1.0 Vp-p ±30% (AC) Connector: BNC, Termination: 50Ω/GND
100 MHz Reference Signal Input (SSC Extension MU181000B-002)	Outputs either 100 MHz with phase deviation x25, x50, or x80 frequency-multiplied clock from Clock Output connector Supports PCI Express Host Refclk input Modulation Frequency: 30 kHz to 33 kHz Level: 0.15 Vp-p to 1.3 Vp-p (AC) Connector: BNC

Signal Quality Analyzer-R MP1900A Specifications

Refer to the [MP1900A Data Sheet](#) for detailed specifications.

Jitter Modulation Source MU181500B

External Clock Input	Frequency Range: 0.800 000 GHz to 15.000 000 GHz Amplitude: 0.4 Vp-p to 1.0 Vp-p Connector: SMA (J), Termination: 50Ω/AC Coupling
Jittered Clock Output	Number of Output: 2 Amplitude: 0.4 Vp-p to 1.0 Vp-p Connector: SMA (f), Termination: 50Ω/AC Coupling
SJ1	Modulation Frequency: 10 Hz to 250 MHz Amplitude: 0 to 2000 UI @Modulation Frequency 10 kHz to 100 kHz 0 to 1 UI @Modulation Frequency 10 MHz to 250 MHz (Different depending on the operating bit rate)
Built-in SJ2	Modulation Frequency: 33 kHz, 87 MHz, 100 MHz, 210 MHz
Spread Spectrum Clocking (SSC)	Modulation Frequency: 28 kHz to 37 kHz Deviation: 0 to 7000 ppm
Random Jitter (RJ)	Bandwidth: 10 kHz to 1 GHz Amplitude: 0 to 0.5 UI (Different depending on the operating frequency)
Bounded Uncorrelated Jitter (BUJ)	PRBS Pattern Length: $2^n - 1$ ($n = 7, 9, 11, 15, 23, \text{ or } 31$) BUJ Rate: 0.1 Gbit/s to 3.2 Gbit/s, 4.9 Gbit/s to 6.25 Gbit/s, 9.8 Gbit/s to 12.5 Gbit/s Filter Type (LPF 3 dB Bandwidth): 50, 100, 200, 300, 500 MHz, Through Amplitude: 0 to 0.5 UI (Different depending on the operating frequency)
External Jitter	Bandwidth: 10 kHz to 1 GHz

Noise Generator MU196050B*1

Number of Channels	1
Frequency (DMI)	Sinusoidal wave: 2 GHz to 10 GHz
Amplitude (DMI*2)	0 to 200 mVp-p (Differential)
Output Control (DMI)	Switchable ON/OFF (DMI/CMI and External Input are mutually exclusive and selectable.) (DMI/CMI can be output simultaneously.)
Frequency (CMI*)	Sinusoidal wave Low Band: 100 MHz to 1 GHz High Band: 1 GHz to 6 GHz
Amplitude (CMI*2)	0 to 250 mVp-p (Single-ended)
Output Control (CMI)	Switchable ON/OFF (DMI/CMI and External Input are mutually exclusive and selectable.) (DMI/CMI can be output simultaneously.)

*1: Δ Always use in combination with the Pick OFF Tee J1793A standard accessory.

*2: Connect a Coaxial Cable J1948A (0.4 m, SMA connector) and a Pick-off Tee J1793A (pick-off path) to the Noise Output, and define the measurement point at the end of the connection where a 34VKF50A and a Coaxial Cable J1821A (0.8 m, K connector) are connected to the OUT terminal of the J1793A.

Noise Generator MU195050A

Number of Channels	2
Insertion Loss	-3 dB
CMI: Common Mode Noise	0.1 GHz to 6 GHz: Sinusoidal wave
DMI: Differential Mode Noise	2 GHz to 10 GHz: Sinusoidal wave
White Noise	10 MHz to 10 GHz
Crest Factor	>5

21G/32G bit/s SI PPG MU195020A

Operation Rate (NRZ)	2.4 Gbit/s to 21 Gbit/s or 32.1 Gbit/s
Number of Channels	1 or 2
Output Amplitude	0.1 Vp-p to 1.3 Vp-p (Single-end) 0.2 Vp-p to 2.6 Vp-p (Differential)
Emphasis	10Tap
Channel Emulator	Normal: Emulates Insertion Loss using S-parameter data Inverse: Performs De-Emphasis compensation for S-parameter Insertion Loss S-Parameter file: S2P,S4P
ISI	Emulates ISI output using CEI-28G/25G Nyquist frequency loss setting Supports loss control in combination with ISI Board J1758A accessory Insertion Loss setting: 1.5 to 25 dB, 0.01 dB step, Nyquist frequency 0 to 25 dB, 0.01 dB step, 1/2 Nyquist frequency
Tr/Tf (20 to 80%)	12 ps (typ.)
Random Jitter	115 fs rms (typ.)
PCIe, USB Link Training	Supported (MX183000A-PL021/PL022/PL025)
Output Connector	K (J)


Signal Quality Analyzer-R MP1900A Specifications

Refer to the [MP1900A Data Sheet](#) for detailed specifications.

21G/32G bit/s SI ED MU195040A

Operation Rate (NRZ)	2.4 Gbit/s to 21 Gbit/s or 32.1 Gbit/s
Number of Channels	1 or 2
Input Attitude	0.05 Vp-p to 1.0 Vp-p (Single-End) 0.1 Vp-p to 2.0 Vp-p (Differential)
Input Sensitivity (Eye Height)	15 mV (28.1 Gbit/s, NRZ) 30 mV/Eye (28.1 Gbaud, PRBS15, PAM4)
CTLE	Peak Frequency: 14, 8, 4 GHz Gain: 0 to -12 dB
Clock Recovery	Yes, supports SSC
PCIe, USB Link Training	Supported (MX183000A-PL021/PL022/PL025)
Input Connector	K (J)

PAM4 PPG MU196020C

Operation Rate	When selecting the Expert BERT application: 2.4 Gbaud to 32.1/58.2/64.2 Gbaud When selecting the BERT for PCIe 1-7 application: 2.4 Gbaud to 64.2 Gbaud
Number of Output	1
Output Amplitude	NRZ: 70 mVp-p to 800 mVp-p, 2 mV step (Single-ended) PAM4: 70 mVp-p to 800 mVp-p, 1 mV step (Single-ended) PAM3: 48 mVp-p to 532 mVp-p, 1 mV step (Single-ended)
Coding	NRZ, PAM4, PAM3
Offset Reference	Vth
Offset	-2.0-Eye Amplitude/2 to +3.3-Eye Amplitude/2 Vth, 1 mV step (Single-ended)
Emphasis	4 Tap
Channel Emulator	Normal: Emulates and outputs a waveform in which a transmission path equivalent to the loaded S-parameters is connected to the PPG output data signal. Inverse: Emulates and outputs a waveform in which the inverse characteristics of a transmission path equivalent to the loaded S-parameters are connected to the PPG output data signal. Intended for use in compensating for transmission path loss. The following graph shows typical limit values for compensable insertion loss. It does not guarantee that all responses emulated from S-parameter files will be compensated in the same manner as the characteristics shown in this graph. 
Independently Variable PAM4 3 Eye	Available, 20% to 50%, 1 mV step (in terms of eye amplitude) (PAM4 amplitude: 0/3 level defined as 100%)
PAM4 Pattern	Standards-compliant patterns for PAM4 mode QPRBS13-CEI, QPRBS31-CEI PRBS13Q, PRBS31Q, SSPRQ, Square Wave QPRBS13, JP03A, JP03B, Transmitter Linearity PRBS13Q(Infiniband), PRBS23Q, PRBS31Q(Infiniband) PRBS31Q(Fiber Channel) etc.
Error Addition	Bit, Error on MSB, Error on LSB, Error on LSB&MSB, RS-FEC Symbol Error, PCIe6 FEC Symbol Error
Tr/Tf (20 to 80%)	Typ. 6.0 ps at 32, 64 Gbaud, when using J1789A Typ. 7.0 ps at 32, 64 Gbaud, when using J1790A 100 GHz bandwidth sampling oscilloscope used
Output Connector	V Connector (J)
Low Residual Jitter (Intrinsic RJ)	≤ 108 fs rms Calculated by the RJ (rms) of the jitter analysis function using a 01 repetition pattern; specified at 64 Gbit/s.
Signal to noise and distortion ratio (SNDR)	PCIe7* (PAM4): typ. 35 dB

*: When performing calibration under the following conditions and removing the residual noise of the oscilloscope:
Amplitude: 0.8 Vp-p/Differential, J1793A Pick OFF Tee used, Test Pattern: PRBS13Q

Signal Quality Analyzer-R MP1900A Specifications

Refer to the [MP1900A Data Sheet](#) for detailed specifications.

PAM4 PPG MU196020A

Operation Rate (PAM4/NRZ)	2.4 Gbaud to 32.1/58.2/64.2 Gbaud (option selection)
No. of Channels	1
Output Amplitude	70 mVp-p to 800 mVp-p (Single-end) 140 mVp-p to 1600 mVp-p (Differential)
Offset	-2 V to +3.3 V
Emphasis	4 Tap, -20 to +20 dB
Channel Emulator	Generates waveform with insertion loss and simulates waveform with corrected insertion loss Set by loading S-Parameter file (S2 P, S4 P)
ISI	Simulates ISI generation waveform Set using loss (-8.00 to 8.00 dB) at CEI-specified Nyquist frequency Used in combination with channel board, such as J1800A/J1758A (optional accessories parts), or Noise Module MU195050A
Independently Variable PAM4 3 Eye	20 to 50% (PAM4 Amplitude 0/3 level = 100%)
PAM4 Pattern	SSPRQ, PRBS13Q, PRBS31Q, RS-FEC, etc.
PAM4 Pattern Error Addition	MSB Error, LSB Error, LSB&MSB Error, RS-FEC Symbol Error, PCIe6 FEC Symbol Error
Tr/Tf (20 to 80%)	8.5 ps (typ., NRZ)
Random Jitter	170 fs rms (typ., NRZ)
Output Connector	V (J)

PAM4 ED MU196040B

Operation Rates (PAM4/NRZ)	2.4 Gbaud to either 32.1 Gbaud, or 58.2 Gbaud (PAM4)/64.2 Gbaud (NRZ) (option selection)
No. of Channels	1
Input Amplitude	NRZ: $\leq 32.1\text{G}$: 0.05 Vp-p to 1.0 Vp-p, $> 32.1\text{G}$: 0.1 Vp-p to 1.0 Vp-p PAM4: $\leq 32.1\text{G}$: 0.3 Vp-p to 1.0 Vp-p, $> 32.1\text{G}$: 0.4 Vp-p to 1.0 Vp-p
Input Sensitivity (Eye Height)	NRZ: 19 mV @ 26.5625 Gbaud, 21 mV @ 53.125 Gbaud PAM4: 23 mV @ 26.5625 Gbaud, 36 mV @ 53.125 Gbaud
Clock Recovery (Option)	2.4 Gbaud to 32.1 Gbaud, 51 Gbaud to 58.2 Gbaud
Equalizer (Option)	Low-frequency Equalizer ($\leq 1\text{ GHz}$, 2 dB typ.) + DFE (1.4 dB typ.)
PAM4 Patterns	SSPRQ, PRBS13Q, PRBS31Q, etc.
PAM4 Counter	MSB, LSB, Symbol 0 to 3 (Option)
Input Connector	V (J)

32G baud NRZ/PAM4 Re-Driver MU196060A

Target Applications	PCIe 4.0: 16.0 Gbit/s, NRZ PCIe 5.0: 32.0 Gbit/s, NRZ PCIe 6.0: 32.0 Gbaud, PAM4 IEEE802.3bs 400GAUI-8 C2M: 26.5625 Gbaud, PAM4
Supported Plug-in Modules	MU196040B PAM4 ED MU195040A 21G/32G bit/s SI ED
Input Amplitude	PAM4: 0.40 to 0.80 Vp-p / Differential BER < 1E-8, 1E-12 (typ.), MCP, SSC 5300 ppm Down spread NRZ: 0.18 to 0.80 Vp-p / Differential BER < 1E-12, MCP, SSC 5300 ppm Down spread
Input/Output Connector	V (f)
LOSS Compensation	PAM4: 14 dB at 16.0 GHz, BER < 1E-6, 1E-9 (typ.), MCP, SSC 5300 ppm Down spread NRZ: 30 dB at 16.0 GHz, BER < 1E-12, MCP, SSC 5300 ppm Down spread
Clock Recovery (option)	With SSC support, PCIe 4.0, 5.0, 6.0

Ordering Information

When ordering, determine the configuration by referencing the selection guide (MP1900A-E-Z-1) and specify the type, model, name, and quantity. The names listed in the chart below are Order Names. The actual name of the item may differ from the Order Name.

MP1900A

Model/Order No.	Name
MP1900A	Main Frame *1 Signal Quality Analyzer-R
G0342A	Standard Accessories ESD DISCHARGER: 1 pc
J1211	POWER CORD. 3M: 1 pc
J1627A	GND connection cable: 1 pc
P0031A	USB Memory: 1 pc
Z0306A	Wrist Strap: 1 pc
—	RJ45 Cap (Cap for Ethernet Port): 1 pc
MX190000A	Signal Quality Analyzer-R Control Software*2
MX183000A	High-Speed Serial Data Test Software*3, *4
MP1900A-110	Retrofit Option Windows10 Upgrade Retrofit*5
MP1900A-ES310	Maintenance Service Three Years Extended Warranty Service
MP1900A-ES510	Five Years Extended Warranty Service

*1: The Windows 10 OS will be installed in all orders from July 1, 2020.

*2: Standard software pre-installed in Signal Quality Analyzer-R MP1900A

*3: Trial software pre-installed in Signal Quality Analyzer-R MP1900A for extending functions with 30-day free trial period following first launch. When requiring the official version after the 30-day trial period, obtain the official license by purchasing the separate MX183000A-PLxx software license. Refer to the software license.

*4: The PAM4 Control function is bundled with the MX183000A as a standard function and can be used without a license.

*5: MP1900A main units running Windows Embedded Standard 7 are retrofitted to Windows 10 using a hardware upgrade. Anritsu destroys the unnecessary, post-upgrade Windows Embedded Standard 7 parts.
For details, contact our sales representative.

MU191000A

Model/Order No.	Name
MU191000A	Module Synthesizer
J1341A	Standard Accessories OPEN: 3 pcs
J1632A	TERMINATOR: 5 pcs
J1624A	COAXIAL CABLE 0.3M (SMA connector): 4 pcs
J1717A	COAXIAL ADAPTOR (SMA-P, SMA-J): 5 pcs
J1759A	Optional Accessories BNC-SMA Connector Cable (1 m)
MU191000A-ES310	Maintenance Service Three Years Extended Warranty Service
MU191000A-ES510	Five Years Extended Warranty Service

MU181000B

Model/Order No.	Name
MU181000B	Module 12.5 GHz 4port Synthesizer
J1624A	Standard Accessories Coaxial Cable 0.3 m (SMA): 4 pcs
MU181000B-002	Option SSC Extension
MU181000B-102	Retrofit Option SSC Extension Retrofit
MU181000B-ES310	Maintenance Service Three Years Extended Warranty Service
MU181000B-ES510	Five Years Extended Warranty Service

MU181500B

Model/Order No.	Name
MU181500B	Module Jitter Modulation Source
J1624A	Standard Accessories Coaxial Cable 0.3 m (SMA): 1 pc
J1508A	BNC-SMA Connector Cable (30 cm): 2 pcs
J1137	Terminator: 6 pcs
J1341A	Open: 2 pcs
Z0897A	MP1800A Manual CD: 1 pc
Z0918A	MX180000A Software CD: 1 pc
MU181500B-ES310	Maintenance Service Three Years Extended Warranty Service
MU181500B-ES510	Five Years Extended Warranty Service

MU196050B

Model/Order No.	Name
MU196050B	Module Noise Generator
J1717A	Standard Accessories COAXIAL ADAPTOR (SMA-P, SMA-J): 4 pcs
J1632A	TERMINATOR: 2 pcs
J1341A	Open: 2 pcs
J1948A	Coaxial Skew Matched Cable Pair (0.4 m, SMA Connector): 2 pcs
J1793A	Pick OFF Tee: 2 pcs
34VKF50A	Optional Accessories Fixed Adapter (V-M, K-F)
J1821A	Coaxial Skew Matched Cable Pair (0.8 m, K Connector)
MU196050B-ES310	Maintenance Service Three Years Extended Warranty Service
MU196050B-ES510	Five Years Extended Warranty Service

MU195050A

Model/Order No.	Name
MU195050A	Module Noise Generator
J1632A	Standard Accessories Terminator (SMA): 4
J1359A	Coaxial Adapter (K-P, K-J, SMA): 4
J1717A	COAXIAL ADAPTOR (SMA-P, SMA-J): 2
J1341A	Open: 6
J1746A	Skew Match Pair Semrigid Cable (K connector, Data Input1): 1 set
J1747A	Skew Match Pair Semrigid Cable (K connector, Data Input2): 1 set
J1792A	Skew Match Pair Semrigid Cable (V-K connector, MU196020A PPG Output to MU195050A Noise Data Input1): 1 set
MU195050A-001	Option White Noise
MU195050A-101	Retrofit Option White Noise Retrofit
MU195050A-ES310	Maintenance Service Three Years Extended Warranty Service
MU195050A-ES510	Five Years Extended Warranty Service

Ordering Information

When ordering, determine the configuration by referencing the selection guide (MP1900A-E-Z-1) and specify the type, model, name, and quantity.

MU196060A*15

Model/Order No.	Name
MU196060A	Module 32G baud NRZ/PAM4 Re-Driver
J1916A	Standard Accessories OPEN (V): 4 pcs
J1341A	OPEN (SMA): 1 pc
J1898A	Coaxial Cable Set for MU196060A: 1 set
	[J1917A Coaxial Semi-rigid Cable: 1
	J1932A Coaxial Skew Matched Cable Pair (0.8 m, V Connector): 1]
MU196060A-001	Option Clock Recovery for SSC
MU196060A-301	Retrofit Option Clock Recovery for SSC Retrofit
MU196060A-ES310	Maintenance Service Three Years Extended Warranty Service
MU196060A-ES510	Five Years Extended Warranty Service

MU195020A

Model/Order No.	Name
MU195020A	Module 21G/32G bit/s SI PPG
J1632A	Standard Accessories Terminator (SMA): 5 pcs
J1341A	Open: 2 pcs
J1359A	Coaxial Adapter (K-P, K-J, SMA): 1 pc
J1717A	COAXIAL ADAPTOR (SMA-P, SMA-J): 6 pcs
MU195020A-001	Option 32G bit/s Extension
MU195020A-010	1ch Data Output
MU195020A-020	2ch Data Output
MU195020A-011	1ch 10Tap Emphasis
MU195020A-021	2ch 10Tap Emphasis
MU195020A-030	1ch Data Delay
MU195020A-031	2ch Data Delay
MU195020A-040	1ch Variable ISI
MU195020A-041	2ch Variable ISI
MU195020A-050	Sequence Editor Function*6
MU195020A-051	Sequence Editor Function PCIe 5 Extension*6
MU195020A-101	Retrofit Options 32G bit/s Extension Retrofit
MU195020A-111	1ch 10Tap Emphasis Retrofit
MU195020A-121	2ch 10Tap Emphasis Retrofit
MU195020A-130	1ch Data Delay Retrofit
MU195020A-131	2ch Data Delay Retrofit
MU195020A-140	1ch Variable ISI Retrofit
MU195020A-141	2ch Variable ISI Retrofit
MU195020A-340	1ch Variable ISI Retrofit
MU195020A-341	2ch Variable ISI Retrofit
MU195020A-350	Sequence Editor Function Retrofit
MU195020A-351	Sequence Editor Function PCIe 5 Extension Retrofit
J1632A	Opt-x10 Accessories Terminator (SMA): 2
J1359A	Coaxial Adapter (K-P, K-J, SMA): 2
J1632A	Opt-x20 Accessories Terminator (SMA): 4
J1359A	Coaxial Adapter (K-P, K-J, SMA): 4
MU195020A-ES310	Maintenance Service Three Years Extended Warranty Service
MU195020A-ES510	Five Years Extended Warranty Service

*6: Option 050 supports PCIe 1 to 4, and USB 3.2 ×1. Option 051 supports PCIe 5.
Option 050 is required when adding Option 051.

MU196020C*13

Model/Order No.	Name
MU196020C	Module PAM4 PPG
J1632A	Standard Accessories TERMINATOR: 4 pcs
J1889A	Terminator (V Connector): 2 pcs
J1341A	OPEN: 2 pcs
J1359A	COAXIAL ADAPTOR (K-P,K-J,SMA): 1 pc
J1717A	COAXIAL ADAPTOR (SMA-P,SMA-J): 5 pcs
MU196020C-001	Option 32G baud*
MU196020C-002	58G baud*
MU196020C-003	64G baud*
MU196020C-011	4Tap Emphasis
MU196020C-030	Data Delay
MU196020C-040	Adjustable ISI
MU196020C-042	FEC Pattern Generation
MU196020C-043	FEC Error Insertion for PCIe6
MU196020C-045	USB4 Gen4 Pattern Generation
MU196020C-050	Inter-Module Synchronization
MU196020C-112	Retrofit Options 32G to 58G baud Retrofit
MU196020C-113	32G to 64G baud Retrofit
MU196020C-123	58G to 64G baud Retrofit
MU196020C-111	4Tap Emphasis Retrofit
MU196020C-130	Data Delay Retrofit
MU196020C-140	Adjustable ISI Retrofit
MU196020C-142	FEC Pattern Generation Retrofit
MU196020C-143	FEC Error Insertion for PCIe6 Retrofit
MU196020C-145	USB4 Gen4 Pattern Generation Retrofit
MU196020C-150	Inter-Module Synchronization Retrofit
MU196020C-340	Adjustable ISI Retrofit
MU196020C-342	FEC Pattern Generation Retrofit
MU196020C-343	FEC Error Insertion for PCIe6 Retrofit
MU196020C-345	USB4 Gen4 Pattern Generation Retrofit
MU196020C-ES310	Maintenance Service Three Years Extended Warranty Service
MU196020C-ES510	Five Years Extended Warranty Service

*: Select any one

Ordering Information

When ordering, determine the configuration by referencing the selection guide (MP1900A-E-Z-1) and specify the type, model, name, and quantity.

MU196020A*15

Model/Order No.	Name
MU196020A	Module PAM4 PPG
	Standard Accessories
J1632A	TERMINATOR: 4
J1889A	TERMINATOR (V): 2
J1341A	OPEN: 2
J1359A	COAXIAL ADAPTOR (K-P,K-J,SMA): 1
J1717A	COAXIAL ADAPTOR(SMA-P,SMA-J): 5
	Option
MU196020A-001	32G baud*
MU196020A-002	58G baud*
MU196020A-003	64G baud*
MU196020A-011	4Tap Emphasis
MU196020A-030	Data Delay
MU196020A-040	Adjustable ISI
MU196020A-042	FEC Pattern Generation
MU196020A-043	FEC Error Insertion for PCIe6
MU196020A-045	USB4 Gen4 Pattern Generation
MU196020A-050	Inter-Module Synchronization
MU196020A-051	Sequence Editor Function
MU196020A-052	Sequence Editor Function for Multi-channel
MU196020A-056	Sequence Editor Function PCIe 6 and CXL 3 Flits Extension*7
MU196020A-060	PCIe6 LEQ
	Retrofit Options
MU196020A-112	32G to 58G baud Extension Retrofit
MU196020A-113	32G to 64G baud Retrofit
MU196020A-123	58G to 64G baud Retrofit
MU196020A-111	4Tap Emphasis Retrofit
MU196020A-130	Data Delay Retrofit
MU196020A-140	Adjustable ISI Retrofit
MU196020A-142	FEC Pattern Generation Retrofit
MU196020A-145	USB4 Gen4 Pattern Generation Retrofit
MU196020A-150	Inter-Module Synchronization Retrofit
MU196020A-160	PCIe6 LEQ Retrofit
MU196020A-156	Sequence Editor Function PCIe 6 and CXL 3 Flits Extension Retrofit*7
MU196020A-340	Adjustable ISI Retrofit
MU196020A-342	FEC Pattern Generation Retrofit
MU196020A-343	FEC Error Insertion for PCIe6 Retrofit
MU196020A-345	USB4 Gen4 Pattern Generation Retrofit
MU196020A-351	Sequence Editor Function Retrofit
MU196020A-352	Sequence Editor Function for Multi-channel Retrofit
MU196020A-356	Sequence Editor Function PCIe 6 and CXL 3 Flits Extension Retrofit*7
MU196020A-360	PCIe6 LEQ Retrofit*8
	Maintenance Service
MU196020A-ES310	Three Years Extended Warranty Service
MU196020A-ES510	Five Years Extended Warranty Service

*7: Option 051 is required when adding Option 056.

*8: Order when MU196020A serial number is 6272477551 or later

*: Select any one

MU195040A

Model/Order No.	Name
MU195040A	Module 21G/32G bit/s SI ED
	Standard Accessories
J1632A	Terminator (SMA): 2
J1341A	Open: 1
J1717A	COAXIAL ADAPTOR (SMA-P, SMA-J): 4
	Option
MU195040A-001	32G bit/s Extension
MU195040A-010	1ch ED
MU195040A-020	2ch ED
MU195040A-011	1ch CTLE
MU195040A-021	2ch CTLE
MU195040A-022	Clock Recovery
	Retrofit Options
MU195040A-101	32G bit/s Extension Retrofit
MU195040A-111	1ch CTLE Retrofit
MU195040A-121	2ch CTLE Retrofit
MU195040A-122	Clock Recovery Retrofit
	Opt-x10 Accessories
J1341A	Open: 3
J1359A	Coaxial Adapter (K-P, K-J, SMA): 2
J1887A	Fixed Attenuator (6 dB, K Connector): 2
	Opt-x20 Accessories
J1341A	Open: 5
J1359A	Coaxial Adapter (K-P, K-J, SMA): 4
J1887A	Fixed Attenuator (6 dB, K Connector): 4
	Maintenance Service
MU195040A-ES310	Three Years Extended Warranty Service
MU195040A-ES510	Five Years Extended Warranty Service

Ordering Information

When ordering, determine the configuration by referencing the selection guide (MP1900A-E-Z-1) and specify the type, model, name, and quantity.

MU196040B*15

Model/Order No.	Name
MU196040B	Module PAM4 ED
	Standard Accessories
J1632A	TERMINATOR: 2
J1889A	TERMINATOR (V): 2
J1341A	OPEN: 2
J1359A	COAXIAL ADAPTOR (K-P,K-J,SMA): 1
J1717A	COAXIAL ADAPTOR (SMA-P.SMA-J): 3
J1888A	Fixed Attenuator 6 dB: 2
	Option
MU196040B-001	32G baud (2.4G to 32.1G)*
MU196040B-002	58G baud (NRZ: 2.4G to 64.2G, PAM4: 2.4G to 58.2G)*
MU196040B-005	64G baud* ¹⁰
MU196040B-011	Equalizer
MU196040B-021	29G baud Clock Recovery (2.4G to 29G)* ⁹
MU196040B-022	32G baud Clock Recovery (2.4G to 32.1G)* ⁹
MU196040B-023	58G baud Clock Recovery Extension (51G to 58.2G)* ⁹
MU196040B-041	SER Measurement
MU196040B-042	FEC Analysis
MU196040B-043	FEC Analysis for PCIe6
MU196040B-051	PCIe Sequence Editor Pattern Analysis
	Retrofit Options
MU196040B-111	Equalizer Retrofit
MU196040B-112	32G to 58G baud Extension Retrofit
MU196040B-115	32G to 64G baud Extension Retrofit* ¹⁰
MU196040B-121	29G baud Clock Recovery Retrofit
MU196040B-122	32G baud Clock Recovery Retrofit
MU196040B-123	58G baud Clock Recovery Extension Retrofit
MU196040B-124	32G baud Clock Recovery Extension Retrofit
MU196040B-125	58G to 64G baud Extension Retrofit* ¹⁰
MU196040B-141	SER Measurement Retrofit
MU196040B-341	SER Measurement Retrofit
MU196040B-342	FEC Analysis Retrofit
MU196040B-343	FEC Analysis for PCIe6 Retrofit
MU196040B-351	PCIe Sequence Editor Pattern Analysis Retrofit
	Maintenance Service
MU196040B-ES310	Three Years Extended Warranty Service
MU196040B-ES510	Five Years Extended Warranty Service

*9: Select at least one option; either Option 021 or 022 is required when adding Option 023.

*10: There are software restrictions when using 64G baud.
For details, consult our business sales representative.

*: Select any one

MU183020A

Model/Order No.	Name
MU183020A	Module 28G/32G bit/s PPG
	Standard Accessories
J1137	Terminator: 3 pcs
J1359A	Coaxial Adaptor (K-P, K-J, SMA): 1 pc
J1341A	Open: 1 pc
J0541E	6 dB Fixed Attenuator: 1 pc
Z0897A	MP1800A Manual CD: 1 pc
Z0918A	MX180000A Software CD: 1 pc
	Options
MU183020A-001	32G bit/s Extension
MU183020A-012	1ch 2 V Data Output
MU183020A-013	1ch 3.5 V Data Output
MU183020A-022	2ch 2 V Data Output
MU183020A-023	2ch 3.5 V Data Output
MU183020A-030	1ch Data Delay
MU183020A-031	2ch Data Delay
	Retrofit Options
MU183020A-101	32G bit/s Extension Retrofit
MU183020A-112	1ch 2 V Data Output Retrofit
MU183020A-113	1ch 3.5 V Data Output Retrofit
MU183020A-122	2ch 2 V Data Output Retrofit
MU183020A-123	2ch 3.5 V Data Output Retrofit
MU183020A-130	1ch Data Delay Retrofit
MU183020A-131	2ch Data Delay Retrofit
	Standard Accessories for MU183020A-x12, x13
J1137	Terminator: 2 pcs
J1359A	Coaxial Adaptor (K-P, K-J, SMA): 2 pcs
	Standard Accessories for MU183020A-x22, x23
J1137	Terminator: 4 pcs
J1359A	Coaxial Adaptor (K-P, K-J, SMA): 4 pcs
	Maintenance Service
MU183020A-ES310	Three Years Extended Warranty Service
MU183020A-ES510	Five Years Extended Warranty Service

Ordering Information

When ordering, determine the configuration by referencing the selection guide (MP1900A-E-Z-1) and specify the type, model, name, and quantity.

MU183040B

Model/Order No.	Name
MU183040B	Module 28G/32G bit/s High Sensitivity ED
J1137	Standard Accessories Terminator: 2 pcs
J1341A	Open: 1 pc
Z0897A	MP1800A Manual CD: 1 pc
Z0918A	MX180000A Software CD: 1 pc
MU183040B-001	Options 32 Gbit/s Extension
MU183040B-010	1ch ED
MU183040B-020	2ch ED
MU183040B-022	2.4G to 28.1G bit/s Clock Recovery
MU183040B-023	25.5G to 32.1G bit/s Clock Recovery
MU183040B-101	Retrofit Options 32 Gbit/s Extension Retrofit
MU183040B-110	1ch ED Retrofit
MU183040B-120	2ch ED Retrofit
MU183040B-122	2.4G to 28.1G bit/s Clock Recover Retrofit
MU183040B-123	25.5G to 32.1G bit/s Clock Recovery Retrofit
J1341A	Standard Accessories for MU183040B-x10 Open: 2 pcs
J1359A	Coaxial Adaptor (K-P, K-J, SMA): 2 pcs
41KC-6	Precision Fixed Attenuator 6 dB: 2 pcs
J1341A	Standard Accessories for MU183040B-x20 Open: 4 pcs
J1359A	Coaxial Adaptor (K-P, K-J, SMA): 4 pcs
41KC-6	Precision Fixed Attenuator 6 dB: 4 pcs
MU183040B-ES310	Maintenance Service Three Years Extended Warranty Service
MU183040B-ES510	Five Years Extended Warranty Service

Software License

Model/Order No.	Name
MX183000A	High-Speed Serial Data Test Software
MX183000A-PL001	Jitter Tolerance Test
MX183000A-PL011	PCIe Link Sequence
MX183000A-PL021	PCIe Link Training* ¹¹
MX183000A-PL022	USB Link Training* ¹²
MX183000A-PL023	USB 3.2 × 2 Link Training* ¹²
MX183000A-PL025	PCIe 5 Link Training* ¹¹
MX183000A-PL026	PCIe 6 Link Training* ¹¹
MX183000A-PL031	DUT Error Counts Import

*11: PL021 supports PCIe 1 to 4.

PL025 supports PCIe 5.

PL026 supports PCIe 6.

Requires PL021 to add PL025.

Requires PL021 and PL025 to add PL026.

*12: PL022 supports USB 3.2 × 1. PL023 supports USB 3.2 × 2. PL022 is required to add PL023.

On Using VISA*¹³

The National Instruments™ (NI hereafter) NI-VISA*¹⁴ software must be installed to use the MX183000A (this product hereafter). We recommend using NI-VISA saved on the product USB memory stick.

Customers may only use NI-VISA saved on the product memory stick. NI-VISA on the memory stick may not be used for other applications with other products.

When uninstalling this product from the controller PC, etc., also uninstall NI-VISA from the USB memory.

*13: Abbreviation for Virtual Instrument Software Architecture. This is I/O software for remote control of measuring instruments via GPIB, Ethernet and USB interfaces.

*14: NI-VISA was developed by National Instruments for VXI Plug&Play Alliance standards compliant I/O interfaces. National Instruments™, NI™, and NI-VISA™ are registered trademarks of National Instruments Corporation.

Ordering Information

When ordering, determine the configuration by referencing the selection guide (MP1900A-E-Z-1) and specify the type, model, name, and quantity.

Optional Accessories

Model/Order No.	Name
J1900A	Passive Low Frequency Equalizer
G0447A	PCIe6 External Re-Driver
J1947A	Bessel Filter
J1632A	Terminator (SMA)
J1889A	TERMINATOR (V)
J1678A	ESD Protection Adapter-K
J1679A	ESD Protection Adapter-V
J1359A	Coaxial Adapter (K-P, K-J, SMA)
34VFK50	Fixed Adapter (V-F, K-M)*15
34VKF50	Fixed Adapter (V-M, K-F)*15
41KC-3	Fixed Attenuator 3 dB
41KC-6	Fixed Attenuator 6 dB
41KC-10	Fixed Attenuator 10 dB
41KC-20	Fixed Attenuator 20 dB
41VA-3	Fixed Attenuator 3 dB
41VA-6	Fixed Attenuator 6 dB
41VA-10	Fixed Attenuator 10 dB
41VA-20	Fixed Attenuator 20 dB
J1887A	Fixed Attenuator (6 dB, K Connector)
J1888A	Fixed Attenuator (6 dB, V Connector)
J1758A	ISI Board
J1800A	ISI Board V
K261	DC Block
K240C	Precision Power Divider
V240C	Fixed Power divider
J1510A	Pick OFF Tee (K)
J1793A	Pick OFF Tee (V)
K241C	Power Splitter
J1748A	Power Splitter (1.5 GHz to 18 GHz, SMA, using MU195020A × 4 to MU181500B connection)
J1624A	COAXIAL CABLE 0.3 m (SMA connector)
J1342A	COAXIAL CABLE 0.8 m (APC3.5 connector)
J1439A	Coaxial cable (0.8 m, K connector)
J1625A	Coaxial Cable 1 m (SMA connector)
J1449A	Measurement kit (J1324A × 2, J1439A × 2, J1625A × 1)
J1550A	Coaxial skew match cable (0.8 m, APC3.5 connector)
J1551A	Coaxial skew match cable (0.8 m, K connector)
J1728A	Electrical Length Specified Coaxial Cable (0.4 m, K connector)*15
J1759A	BNC-SMA Connector Cable (1 m)
J1741A	Electrical Length Specified Coaxial Cable (0.8 m, K Connector)*15
J1789A	Electrical Length Specified Coaxial Cable (0.4 m, V connector)*15
J1790A	Electrical Length Specified Coaxial Cable (0.8 m, V connector)*15
J1792A	Skew match pair semirigid cable (V-K connector, MU196020A PPG Output to MU195050A Noise Data Input1)
J1821A	Coaxial Skew Matched Cable Pair (0.8 m, K Connector)
J1898A	Coaxial Cable Set for MU196060A
J1917A	Coaxial Semi-rigid Cable
J1932A	Coaxial Skew Matched Cable Pair (0.8 m, V Connector)
J1948A	Coaxial Skew Matched Cable Pair (0.4 m, SMA Connector)
J1761A	PCIe Reference Clock Cable Kit
Z2025A	PCIe CBB Controller
Z2029A	PCIe Reference Clock Buffer

Model/Order No.	Name
AH54192A	56Gbaud Differential Linear Amplifier
W3911AE	MP1900A Operation Manual
W3913AE	MX190000A Operation Manual
W3813AE	MX183000A Operation Manual
W3915AE	MU195020/40/50A Operation Manual
W3976AE	MU196020/40A OPERATION MANUAL
B0576A	Blank Panel
B0736A	Front Cover (For MP1900A)
B0737A	Carrying Case (For MP1900A, with B0736A)
B0738A	Rack Mount Kit (For MP1900A)
Z1746A	Stylus
Z0541A	USB Mouse
J0008	GPIB CABLE, 2.0 m
Z0917A	Shielded LAN Cable, 5 m
Z1953A	Gigabit Ethernet Switch (5 Port)
Z0306A	Wrist Strap
Z1964A	Torque Wrench (Right Angle)

Ordering Information


When ordering, determine the configuration by referencing the selection guide (MP1900A-E-Z-1) and specify the type, model, name, and quantity.

J1815A MP1900A PCIe Measurement Component Set

The following table lists the component set required by the PCIe 3/4/5 Tx/Rx LEQ test.


Item	Description	Qty.	Remarks		
Optional Accessories	MP1900A PCIe Measurement Component Set	1	J1815A		
			Accessories		Qty. Comment
			Coax skew match cable, 0.8 m K connector		4 Junflon J12J103220-00-1
			AE-TMC-10205		2 Coax cable, 1 m, SMA connector
			PICK OFF TEE		2 Anritsu 3-68231
			SMPF-SMAJ-TFLEX-10CM-5PS		3 SMP to SMA adapter cable
			BNC-SMA cable		2
			K261		2 DC Block
			K241C		2 Power Splitter

*15: We recommend using either the J1789A or J1790A as the coaxial cable for the MU196020A/C data output. Recommend using coaxial cable J1789A for MU196040B Data IN. The MU196020A/C data output specifications are defined based on the performance observed using a 70-GHz bandwidth oscilloscope connected as shown below.



Solution except above

The MU196020A/C Data OUT and MU196040B Data IN connectors, and the J1789A/J1790A cables all use V-connectors. Consequently, for K-connectors, use 34VFK50 adapters as shown in the following figure.




PCIe and Ethernet (26.5625 Gbaud) Solution

VK adapter


Use the 34VFK50 or 34VKF50 adapter that matches the DUT connector shape, as shown below.

- MU195050A: K connector output
- MU196060A: V connector input
- When the DUT connector shape is V and a V cable is used: **Two 34VFK50 adapters**
- When the DUT connector shape is K and a K cable is used (e.g., PCIe5 CEM Fixture): **Two 34VKF50 adapters**
- When used in combination with an SI ED: **Two separate 34VFK50 adapters** in addition to the above

With V-conector DUT



With K-conector DUT



G0447A

Install the G0447A between DUT and MU196060A, as shown below. Connect the G0447A and MU196060A using the J1789A.

J1900A

Connect the J1900A to Data Input and Data Input of the MU196040B, as shown below.

For details of the G0447A and J1900A, contact us.



Specifications are subject to change without notice.

• **United States**

Anritsu Americas Sales Company

490 Jarvis Drive, Morgan Hill, CA 95037-2809, U.S.A.
Phone: (408)-778-2000

• **Canada**

Anritsu Electronics Ltd.

Americas Sales and Support

490 Jarvis Drive, Morgan Hill, CA 95037-2809, U.S.A.
Phone: +1-800-Anritsu (1-800-267-4878)

• **Brazil**

Anritsu Eletrônica Ltda.

Praça Amadeu Amaral, 27 - 1 Andar
01327-010 - Bela Vista - São Paulo - SP, Brazil
Phone: +55-11-3283-2511

• **Mexico**

Anritsu Company, S.A. de C.V.

Blvd Miguel de Cervantes Saavedra #169 Piso 1, Col. Granada
Mexico, Ciudad de Mexico, 11520, MEXICO
Phone: +52-55-4169-7104

• **United Kingdom**

Anritsu EMEA Limited

900 Capability Green, Luton, Bedfordshire, LU1 3LU, U.K.
Phone: +44-1582-433200

• **France**

Anritsu SA

12 avenue du Québec, Immeuble Goyave,
91140 VILLEBON SUR YVETTE, France
Phone: +33-1-60-92-15-50

• **Germany**

Anritsu GmbH

Nemetschek Haus, Konrad-Zuse-Platz 1,
81829 München, Germany
Phone: +49-89-442308-0

• **Italy**

Anritsu S.R.L.

Spaces Eur Arte, Viale dell'Arte 25, 00144 Roma, Italy
Phone: +39-6-509-9711

• **Sweden**

Anritsu AB

Kistagången 20 B, 2 tr, 164 40 Kista, Sweden
Phone: +46-8-534-707-00

• **Finland**

Anritsu AB

Technopolis Aviapolis, Teknobulevardi 3-5 (D208.5),
FI-01530 Vantaa, Finland
Phone: +358-20-741-8100

• **Denmark**

Anritsu A/S

c/o Regus Winghouse, Ørestads Boulevard 73, 4th floor,
2300 Copenhagen S, Denmark
Phone: +45-7211-2200

• **Austria**

Anritsu EMEA GmbH

Am Belvedere 10, A-1100 Vienna, Austria
Phone: +43-(0)1-717-28-710

• **United Arab Emirates**

Anritsu A/S

Office No. 164, Building 17, Dubai Internet City
P. O. Box – 501901, Dubai, United Arab Emirates
Phone: +971 (0) 4-2424919

• **India**

ANRITSU INDIA PRIVATE LIMITED

6th Floor, Indiqube ETA, No.38/4, Adjacent to EMC2,
Doddanekundi, Outer Ring Road, Bengaluru – 560048, India
Phone: +91-80-6728-1300
Fax: +91-80-6728-1301

• **Singapore**

ANRITSU PTE LTD

1 Jalan Kilang Timor, #07-04/06 Pacific Tech Centre
Singapore 159303
Phone: +65-6282-2400

• **Vietnam**

ANRITSU COMPANY LIMITED

16th Floor, Peakview Tower, 36 Hoang Cau Street, O Cho Dua Ward,
Hanoi, Vietnam
Phone: +84-24-3201-2730
Fax: +84-24-3201-2740

• **P.R. China (Shanghai)**

Anritsu (China) Co., Ltd.

Room 2301-2303, Tower A, New Caohejing International Business
Center No. 391 Gui Ping Road, Shanghai, 200233, P.R. China
Phone: +86-21-6237-0898

• **P.R. China (Hong Kong)**

ANRITSU COMPANY LIMITED

Unit 1302, 13th Floor, New East Ocean Center,
No.9 Science Museum Road, TsimShaTsui East,
Kowloon, Hong Kong
Phone: +852-2301-4980

• **Japan**

ANRITSU CORPORATION

8-5, Tamura-cho, Atsugi-shi, Kanagawa, 243-0016 Japan
Phone: +81-46-296-1244
Fax: +81-46-296-1239

• **Korea**

Anritsu Corporation Limited

8F, A TOWER, 20, Gwacheondaero 7-gil, Gwacheon-si,
Gyeonggi-do, 13840, Republic of Korea
Phone: +82-2-6259-7300

• **Australia**

Anritsu Pty Ltd

Unit 20, 21-35 Ricketts Road, Mount Waverley, Victoria 3149, Australia
Phone: +61-3-9558-8177

• **Taiwan**

ANRITSU COMPANY, INC.

7F, No. 316, Sec. 1, NeiHu Rd., Taipei 114, Taiwan
Phone: +886-2-8751-1816